


# RHINO T80



## At a glance

Android 13.0  
Android 14 (Coming Soon!)  
4GB (3GB Option) RAM  
32GB Storage  
Global LTE  
EMM validated

## Getting started

| Doc           | Description                          |
|---------------|--------------------------------------|
| Quickstart    | Get started with your device quickly |
| Device manual | Learn how to use your T80 in detail  |

## Device spec

|                             |   |
|-----------------------------|---|
| <b>Display</b>              | 8" HD<br>205 PPI<br>TFT LCD with IPS panel<br>Brightness up to 380cd/m2<br>800x1280 resolution<br>Viewing angles 80°/80°(v/h)<br>16.7m colours<br>16:10 aspect ratio<br>60Hz refresh rate<br>5 touch points |
| <b>Memory &amp; storage</b> | 4GB (3GB Option)<br>32GB  |
| <b>Processor</b>            | Snapdragon 680 SM6225 Octacore 2.4GHz   |
| <b>Battery</b>              | 5100mAh Li-ion<br>Quick Charge 2.0, 18W, PD<br>36 hours typical use<br>18 days standby  |

|                       |  |
|-----------------------|--|
| <b>SIM</b>            | Nano-SIM & eSIM  |
| <b>Ports</b>          | SIM<br>MicroSD up to 1TB<br>USB Type C, USB 2.0<br>3.5mm jack  |
| <b>Audio</b>          | Microphone<br>Stereo Speaker   |
| <b>Connectivity</b>   | 3G: 1 2 4 5<br>4G: 1 2 3 4 5 7 12 13 14 17 18 19 20 25 26 29 30 41 66 71<br>Wi-Fi 802.11 a/b/g/n/ac<br>Bluetooth 5.1<br>NFC<br>Location: GPS, A-GPS, Galileo, QZSS   |
| <b>Camera</b>         | 5MP AF front<br>8MP FF rear  |
| <b>Sensors</b>        | Accelerometer<br>eCompass<br>Ambient light sensor<br>Proximity sensor<br>SAR   |
| <b>Environmental</b>  | Functional up to 95% humidity<br>0c to 40c typical operating temp<br>Unboxed(LHW): 205.8mm x 128mm x 9.8mm<br>IP52 rated<br>0.5m drop-tested   |
| <b>Certifications</b> | FCC<br>CE<br>UKCA<br>PTCRB<br>Google Play Protect<br>AT&T Network Optimized<br>AT&T FirstNet Ready<br>Android Enterprise Recommended<br>T-Mobile Network Certified for IoT Non-stock<br>Certified for Verizon Business |

### **Certification Documentation**

DoC-CE

## **Product lifecycle**

For product support and lifecycle status, please see the [security](#) page.

## Warranty information

All RHINO hardware comes with a 1 year limited warranty. For detailed warranty information, please see [RHINO Warranty](#).